

Mighty Mite Killer Quick Start Guide

- A. Have 110 volt power available.
- B. Slide the unit into the front entrance of the hive and immediately tape the custom closure stick on both ends to the bottom board. if this is a strong hive I recommend you tape across the top of the stick to the hive body. The bees will try to push this stick off the front landing board.
- C. Remove Honey Supers and install the internal sensor on the top of the center brood frame in the bottom hive body or super if your using it for raising brood and add the Styrofoam insulation sheet. Place the honey supers back in place on top of the insulation sheet.
- D. Connect the power, you will see a solid light it can be one of three colors (red, green, blue) this indicates power is on and ready.
- E. Push the mode button located in the center of the controller firmly.
- F. You will now have a flashing blue light (raising the temperature).
- G. Upon reaching mite temp. set point you will have a green flashing light.
- H. Remove the special closure stick.
- I. If the unit cycles back to the blue flashing light add a standard reducer stick with the large 3 inch opening.
- J. Cycle is complete after 2-1/2 hours with a solid green & blue light.
- K. Remove insulation sheet.
- L. Remove the Mighty Mite Killer.
- M. You probably will find dead mites, small hive beetles, etc. on the white alum. plate.

Always call first with any questions.

Lynn Williams

803-504-9313